

Renovia Zone Amplifier (NV-RVZA50S).

Specifications

Power Supply Power Requirements

Power Input	95-130VAC 60Hz
Power Consumption Maximum	85W
Power Consumption Average*	15W
Power Consumption No Signal*	6W
Power Supply Outlet	25VDC at 1.4A cont. , 2.6A peak
Efficiency	84%

* With no Control Pad device connected.

Average is measured at 1/8 max power (3.125W/channel)

Power Supply Regulatory Approvals

UL
FCC

Power Supply Physical Specifications

Unit Size (mm)	114 H x 95 W x 64 D
Unit Size (inch)	4 1/2 H x 3 3/4 W x 2 1/2 D

Local Source Audio Input/Line Output

RJ45 Digital to Line In/Out Accessory

NuVoNet

Local NuVoNet Control Pad RJ45

Speaker Output

Stereo Plug with screw terminals
Impedance 4 to 8 ohm

Amplifier Output

Power Out (1% THD into 8 ohm) 2 x 25W
Frequency Response (20 - 20kHz) ±3dB

Regulatory Approvals

UL
FCC

Physical Specifications

Unit Size (mm)	117 H x 120 W x 22 D
Unit Size (inch)	4 5/8 H x 4 3/4 W x 7/8 D
Shipping Size (mm)	203.2 H x 228.6 W x 177.8 D
Shipping Size (inch)	8 H x 9 W x 7 D
Unit Weight (kg)	0.50
Unit Weight (lbs)	1.1
Shipping Weight (kg)	0.91
Shipping Weight (lbs)	2

NuVo reserves the right to change specifications without notice.

Office Toll Free: 866.796.4904

Office Direct: 859.817.7200

Email: sales@nuvotechnologies.com

Web: www.nuvotechnologies.com